


What's MAC address clone used for and how to configure ?

It is suitable for : **N100RE, N150RH, N150RT, N151RT, N200RE, N210RE, N300RT, N301RT , N300RH, N302R Plus, A702R, A850, A3002RU**

Application introduction: MAC address is the physical address of your computer's network card. Generally, every network card has one unique Mac address. Since many ISPs only allow one computer in LAN to access Internet, users can enable MAC address clone function to make more computers surf Internet.

STEP-1:

Connect your computer to the router by cable or wireless, then login the router by entering http://192.168.0.1 into the address bar of your browser.



Note:

The default access address varies depending on the actual situation. Please find it on the bottom label of the product.

STEP-2:

User Name and Password are required, by default both are **admin** in lowercase letter. Click **LOGIN**.

USER LOGIN

[Forget Password?](#)

A user login form with a light gray background. At the top right is a link 'Forget Password?'. Below it is a white box containing two input fields. The first field is labeled 'User Name' and contains the text 'admin'. The second field is labeled 'Password' and contains six black dots. Below the input fields is a large blue button with the text 'LOGIN' in white.

STEP-3:

Click **Network->WAN Settings** , Select the WAN type and click **Scan MAC Address**.

Finally click Apply.

WAN Settings

A screenshot of the WAN Settings configuration page. The page has a light gray background. On the left side, there is a list of settings: WAN Type, User Name, Password, Confirmed Password, Service Name, AC Name, WAN DHCP Type, DNS Type, Connection Type, MTU, Clone MAC Address, Web Server Port, and several checkboxes for features like uPNP, NetSniper, IGMP Proxy, IGMP Snooping, Ping Access, Web Server Access, and IPsec pass through. On the right side, there are input fields and radio buttons for these settings. A red box labeled '1' highlights the WAN Type dropdown menu, which is currently set to 'PPPoE/Dual WAN Access PPPoE'. Below it are three empty input fields for User Name, Password, and Confirmed Password. A red box labeled '2' highlights the 'Scan MAC Address' button, which is next to the 'Clone MAC Address' field containing the value '909f33e85922'. A red box labeled '3' highlights the 'Apply' button at the bottom left of the page.