

N600R Multiple SSID settings


It is suitable for : **N600R, A800R, A810R, A3100R, T10, A950RG, A3000RU**

Application introduction:

Solution about how to configure multiple SSID for TOTOLINK products.

STEP-1:

Connect your computer to the router by cable or wireless, then login the router by entering http://192.168.0.1 into the address bar of your browser.



Note:

The default access address varies depending on the actual situation. Please find it on the bottom label of the product.

STEP-2:

User Name and Password are required, by default both are **admin** in lowercase letter. Click **LOGIN**.

USER LOGIN

[Forget Password?](#)

👤
User Name

🔑
Password

STEP-3:

Please go to **FWireless ->Multiple APs** page, and check which you have selected. Select **Enable**, then Input your own **SSID and Key**, then Click **Add**. So you can repeat this operation for Multiple SSID.

TOTO LINK
The Smartest Network Device

N600R (Firmware V5.3c.3243)

- System Status
- Operation Mode
- Network +
- Wireless -
- Wireless Status
- Basic Setting
- Multiple APs 2
- MAC Authentication
- WDS Setting
- WPS Setting
- Advanced Setting
- Wireless Schedule
- QoS +
- Firewall +
- Management +

Multiple APs

This page shows the wireless setting for multiple APs.

SSID 1

SSID Broadcast 3

Encryption 4

Encryp Type

Key Format

Key 4

5

Multiple APs List (The maximum AP count is 2)

ID	SSID	Encryption	Select