

# 170 How to set up the router to work as a AP mode?

# It is suitable for : N100RE, N150RT , N200RE, N210RE, N300RT, N302R Plus, A3002RU

## **Application introduction**

AP mode, connect the superior AP/Router by wire, you can bridge the superior's AP/Router wired signal into wireless Wi-Fi signals for Wi-Fi devices. Here we take A3002RU for demonstration. Note: Confirm that your wired network can share the Internet.



### Set up steps

### STEP-1:

Connect your computer to the router by cable or wireless, then login the router by entering http://192.168.0.1 into the address bar of your browser.

$\left( \leftarrow  ightarrow$ C' $\bigtriangleup$	Q 192.168.0.1			$\rightarrow$

Note: The default access address varies depending on the actual situation. Please find it on the bottom label of the product.

### STEP-2:

User Name and Password are required, by default both are admin in lowercase letter. Click LOGIN.

## USER LOGIN

Forget Password?

2	User Name	admin
۶	Password	•••••

### STEP-3:

Enter the **Advanced Setup** page of the router, then follow the steps illustrated. (1)Click **Operation Mode**>(2)Select **AP Mode**->(3)Click **Apply** button

TOTO The Smartest Netwo	LINK vork Device		The Smartest Network Device
Model No. A3002RU (Firmy	ware V1.0.4)		Easy Setup Reboot Help
💬 Status		Operation Mode	
Operation Mode		1	Operation Mode Help
Network	•	Router Mode	In this mode, the device is supposed to connect to the internet via ADSL/Cable modem. The WAN type can be setup on WAN page, including PPPOE, DHCP Client, PPTP Client,
IPv6 Network	•		L2TP Client and Static IP.
Wireless 5GHz	•	Repeater(Extender)	This mode extends your existing wireless network to wider coverage. You can access the the Internet by wireless or wired connection to the device
Wireless 2.4GHz	•	AP Mode	Combine two local networks via wireless connection. You can only connect to the device by cable.
💠 QoS		WISP Mode	In this mode, the device connect to WISP Station wirelessly through PPPOE/DHCP Clien/PPTP Client/LTP Client/Static IP WAN types. You are able to share Internet via
Firewall	•		local wireless and wired network
USB Share			WAN Interface wan 5GHz *
System	•		
		Apply/Next>>	

#### Copyright(C)2017 TOTOLINK Ltd, All Rights Reserved

#### STEP-4:

Next set the wireless SSID and password. Finally click Connect.

The Smartest Network I	Device	The Smartest Network De
lodel No. A3002RU (Firmware	V1.0.4)	Easy Setup Reboo
Status	Basic Settings	
Operation Mode	Basic Settings	Enabled V
Network	+ SSID	TOTOLINK_A3002RU_5G
IPv6 Network	+ Broadcast SSID	Enabled V
Wireless 5GHz	+ Encryption	WPA2 7 2
Wireless 2.4GHz	+ Limit Client AP(3-64)	64 Set 5G wireless SSIE
QoS	Download:	0 Mbps (0:Unlimit) password
irewall	t Upload:	0 Mbps (0:Unlimit)
ISB Share	Authentication Mode	Enterprise (RADIUS)      Personal (Pre-Shared Key)
System	WPA2 Cipher Suite	□ TKIP     AES
system	Pre-Shared Key Format  Pre-Shared Key	Passphrase
TOTO LIN The Smartest Network D	NK.	117 TOTOLINK Ltd, All Rights Reserved The Smartest Network Devi
The Smartest Network D	<b>NK</b> Device	
The Smartest Network D	<b>NK</b> Device	The Smartest Network Dev
The Smartest Network D lel No. A3002RU (Firmware N Status	<b>Device</b> /1.0.4)	The Smartest Network Dev
The Smartest Network D el No. A3002RU (Firmware N tatus Operation Mode	Vice /1.0.4) Basic Settings	The Smartest Network Devi Easy Setup Reboot
The Smartest Network D el No. A3002RU (Firmware N itatus Operation Mode letwork	Vice V1.0.4) Basic Settings Basic Settings	The Smartest Network Devi Easy Setup Reboot Enabled T
The Smartest Network D el No. A3002RU (Firmware V itatus operation Mode letwork Pv6 Network	Vice (1.0.4) Basic Settings Basic Settings SSID	The Smartest Network Dev Easy Setup Reboot Enabled T TOTOLINK_A3002RU
The Smartest Network D el No. A3002RU (Firmware N tatus operation Mode letwork Pv6 Network //ireless 5GHz	VI.0.4) Basic Settings Basic Settings SSID Broadcast SSID	The Smartest Network Devi Easy Setup Reboot Enabled TOTOLINK_A3002RU Enabled TOTOLINK_A3002RU Enabled TOTOLINK_A3002RU
The Smartest Network D el No. A3002RU (Firmware N tatus peration Mode etwork Pv6 Network /ireless 5GHz /ireless 2.4GHz	Vi.0.4)  Basic Settings Basic Settings SSID Broadcast SSID Encryption Limit Client AP(3.64)	Easy Setup Reboot Enabled TOTOLINK_A3002RU Enabled TOTOLINK_SOUCH WPA2 T 5
The Smartest Network D el No. A3002RU (Firmware N tatus peration Mode etwork v6 Network /ireless 5GHz /ireless 2.4GHz oS	Vice         /1.0.4)         Basic Settings         Basic Settings         SSID         Broadcast SSID         Encryption         Limit Client AP(3-64)         Download:         Upload:	The Smartest Network Devi Easy Setup Reboot Enabled TOTOLINK_A3002RU Enabled TOTOLINK_A3002RU Enabled Set 2.4G wireless St 64
The Smartest Network D el No. A3002RU (Firmware N tatus peration Mode etwork v6 Network /ireless 5GHz /ireless 2.4GHz oS	Vice V1.0.4) Basic Settings Basic Settings SSID Broadcast SSID Encryption Limit Client AP(3-64) Download:	The Smartest Network Devi Easy Setup Reboot TOTOLINK_A3002RU Enabled V WPA2 V 64 0 Mbps (0:Unlimit) Set 2.4G wireless SS and password
	V1.0.4)         Basic Settings         Basic Settings         SSID         Broadcast SSID         Encryption         Limit Client AP(3-64)         Download:         Upload:	Easy Setup Reboot Easy Setup Reboot Enabled T TOTOLINK_A3002RU Enabled WPA2 5 64 0 Mbps (0:Unlimit) 0 Mbps (0:Unlimit)



Copyright(C)2017 TOTOLINK Ltd, All Rights Reserved

#### STEP-5:

Congratulations! Now all your Wi-Fi enabled devices can connect to the customized wireless network.

#### Note:

After the AP mode is set successfully, you cannot log in to the management page. If you need to make changes, please Reset the router.